

Hooft-Santorini Generalized Response and Calibration Factor

These calculations are for the generalized case and assume the signal is in the sensor frequency range giving a flat response. Frequency response ranges are indicated.

SENSOR RESPONSE INFO:

For the High-Tech Hydrophone sensitivity:

For the custom High-Tech Hydrophone (HTI-90-U) the manufacturer calibration files give a sensitivity of -182.7 dB re 1V/μPa. This hydrophone loses ~2 dB in sensitivity per ~6000m in depth (10,000 psi) so for typical ocean depth around 3km we correct ~1 dB and use -183.7 dB re 1V/μPa. Using amplitude spectra throughout (e.g. $X[db] = 20 \cdot \log_{10}[X/Xref]$), this gives $S(hyd-HTI) = 10^{**(-183.7/20)} \cdot 1V/\mu Pa = .653 \text{ mV/Pa}$ (@ 3000m water depth). Thus:

S(hyd-HTI) = 0.653 mV/Pa -or- (6.53e-4 V/Pa)

flat response: 0.05 Hz to 7.5 kHz (@ 3000m depth)

Frequency response information:

From Brian Spychalski at High Tech Inc. (personal communication: June 03, 2014):

1: HPF at input of preamp created by ceramic element 12.8nF (nom.) and 300 meg ohm resistor (0.04Hz)

2: There is another HPF at opamp set at 0.02Hz.

3: LPF at opamp is set at 7.5KHz.

Parameter	Nominal Value	Units
Zeros (2)	0 0	Rad/s
Poles (3)	-24.127431 -0.1256637 -47124	Rad/s
Normalization	47124	
Normalization Frequency	500	Hz

For the L28LB tri-axial seismometer sensitivity:

Transduction constant --> $1.57 \cdot \sqrt{R-coil}$ V/m/s with R-coil = 630 ohm nominally this gives 39.53 V/m/s. SIO uses 70% coil current damping, (R-shunt-ss = (7860+51) ohm single-sided, divide by 2 to effective R-shunt damping for differential signal), thus R-shunt-diff = 3956 ohm, which gives:

S(L28) = 34.10 V/m/s

flat response: ~4.5 Hz and above

Frequency response information (for a damped oscillator):

Two zeros at 0, two poles at $\omega_0 \left(\delta \pm i\sqrt{1-\delta^2} \right)$ where $\delta = 0.701$ (damping value).

Parameter	Nominal Value	Units
Zeros (2)	0 0	Rad/s
Poles (2)	19.820 +/- i*20.164	Rad/s
Normalization	-1	
Normalization Frequency	4.5	Hz

